

TASKalfa 620 / TASKalfa 820

PRODUCT LIBRARY 1.0 EUR

Release Notes

April 14, 2009

CD Contents

Printer Drivers	Version	Windows 98, Me, NT4.0	Windows 2000	Windows XP	Windows Vista	Windows Server 2000 Server 2003	Windows Server 2008
KX Printer Driver (Generic)	4.2.1409b	✓					
KX Printer Driver	5.0.1219		✓	✓	✓	✓	✓
PCL Mini Driver (Generic)	3.2	✓					
PCL Mini Driver	4.2		✓	✓		✓	
PCL Mini Driver (Vista)	1.2				✓		✓
KPDL Mini Driver (Generic)	8.4 [9-4-2007]	✓					
KPDL Mini Driver	8.4 [11-12-2008]		✓	✓	✓	✓	✓
Novell NDPS (Generic)	4.2.1409b	✓					
Novell NDPS	5.0.1219		✓	✓*			

Scanner Drivers	Version	Windows 2000	Windows XP	Windows Vista	Windows Server 2000 Server 2003	Windows Server 2008
TWAIN Source	1.28	✓	✓	✓	✓	✓

Utilities	Version	Windows 2000	Windows XP	Windows Vista	Windows Server 2000 Server 2003	Windows Server 2008
KM-NET VIEWER***	4.6.1225	✓	✓	✓	✓	✓
KM-NET for Direct Printing	2.3.1113	✓	✓	✓	✓	✓
KPrint	5.1.8	✓	✓*		✓*	

Quick Network Setup	2.0.7	✓	✓*	✓	✓*	
Driver Deleter	2.9.2619	✓	✓			
Scanner File Utility	3.17.11	✓	✓	✓	✓	✓
DB Assistant	1.8.4	✓	✓	✓	✓	✓
Address Book	1.30	✓	✓	✓	✓	✓
Address Editor	1.50	✓	✓	✓	✓	✓

(*) Supports 32-bit version of Windows operating systems only.

(**) Supports 64-bit version of Windows operating systems only.

(***) Does not support local connection.

➤ For **Mac OS 9** and **OS X**, install PPD Driver version 8.4 [11-12-2008].

➤ For **Linux**, install PPD Driver version 8.4 [11-12-2008].

Note: There are no known issues for Mac OS 9, Mac OS X or Linux.

On the CD, KPrint is in the \Network\ folder and Driver Deleter and Driver Info in the \Utilities\ folder.

Windows 98, Me, and NT 4.0

Install generic printer drivers with the **Add Printer** wizard.

1. Click **Start** in the Windows taskbar.
2. Click **Settings**.
3. Click **Printers**.
4. Click **Add a printer** in the **Printer Tasks** group box on the left.
5. The **Add a Printer** wizard page appears. Click **Next** and follow the instructions.
6. Browse through the CD to locate the appropriate Oempsetup.inf file.
7. When the **Completing the Add Printer Wizard** page appears, click **Finish**.

Driver Type	Windows 98/Me location on CD	Windows NT 4.0 location on CD
KX Driver	\PrnDr\KXDriver\Win9x_Me	\PrnDr\KXDriver\WinNT_2K
PCL Mini Driver	\PrnDr\PCL 5e UniDriver\Win9x_Me \(language)	\PrnDr\PCL 5e UniDriver\WinNT4 \(language)
KPDL Mini Driver	\PrnDr\KPDL Mini-driver\Win9x_Me \(language)	\PrnDr\KPDL Mini-driver\WinNT4 \(language)

- Kyocera generic printer drivers do not support the Post Installer.

Known Issues:

All Windows Operating Systems

The CD menu may not launch properly if the Windows operating system is not updated with the latest service packs and critical updates.

Solution: Update the Windows operating system with the latest service packs.

KM-NET VIEWER may not install correctly on PCs using Microsoft Windows Installer before 3.1 v2.

Solution: Update to the latest service pack and install the latest Microsoft Windows Installer.

When updating a utility using the CD Software Installer, the utility installed incorrectly. This is a known issue with the Microsoft Windows Installer.

Solution: Uninstall the previous version of the utility before installing the new one.

If the KX Driver is uninstalled immediately after installation, the uninstallation fails.

Solution: Restart the PC and uninstall the KX Driver.

Status Monitor is not available from the client side in a server-client environment on Microsoft Windows Server 2000, 2003, and 2008.

Windows 2000 / 2003

On a Windows 2000 client using a 64-bit Windows 2003 server, a shared PCL minidriver will display an error with the display of Printer Properties or Printing Preferences. The message will read "Printer Properties cannot be displayed" or "Printer Preferences cannot be displayed." Microsoft has acknowledged that this is a known issue with the 64-bit version of Windows Server 2003.

Solution: Use a 32-bit Windows XP Client with the 64-bit Windows 2003 Server. Install the shared printer on the Windows XP client and set the Printer Properties and Printing Preferences from the Windows XP Client.

KM-NET VIEWER will not install on some Windows 2000 and Windows 2003 Server operating systems.

Solution: Update to the latest service packs or install the Microsoft SOAP Toolkit 3.0.

Windows XP / Vista

Although a user has administration privileges on a machine, the user may not have admin privileges on for a printer running on that machine.

Solution: Run the driver in administrator mode by choosing "Run as Administrator".

Driver Deleter and KM Uninstaller will not remove printer drivers installed with the Add Print Wizard.

Solution:

1. Reboot the PC. If this is not possible, make sure that all applications using the driver are closed.
2. Delete the printers from the Printer Manager.
3. Close all Printer Property boxes.
4. Right-click on a blank spot in the printer manager to access Printer Server Properties.
5. Select **Run as Administrator**.
6. Select **Printer Server Properties**.
7. On the Driver tab, highlight all drivers that you wish to remove and click on **Remove**.
8. On the pop-up dialogue, select **Remove Driver** and **Driver Package**.
9. Click OK on the rest of the screens until you can see that the driver has been removed.

Windows XP / Vista, KX Driver Only

EMF (enhanced metafile) spooling is not supported for KPDLE printing.

Status Monitor is not supported on the client side for the Client/Server environment.

HTML Help is supported only in English and Japanese.

An extra blank page prints when a Microsoft Word 2007 document is printed when both Mixed Paper Sizes and Duplex is selected. This is a known limitation in Word 2007.

Some objects in PowerPoint 2007 do not print in Poster mode for 3x3 pages or more. This is a known limitation in PowerPoint 2007.

In Vista, Custom Paper Size is missing from the Paper Size list of Windows Photo Gallery. This is a known limitation in the Photo Printing Wizard (PPW) application.

Interactive services dialog detection messages pop-up when printing mixed sized documents in booklet mode on the 64-bit version of Vista.

When adding a 32-bit driver to a shared printer on a server running a 64-bit version of Windows, the model name may appear multiple times in *Share this Printer*.

Solution: To avoid displaying multiple model names, choose "Have Disk" when using the "Additional Drivers..." option and browse to the x86 driver INF file for the desired model to install it.

Windows Vista, KPDL and PCL Mini-drivers Only

Some KPDL mini-driver features may be selected without the associated peripheral device attached to the printer.

Solution: Verify that the associated peripheral device is attached to the printer before using the feature.

If any of the Device Settings are manually changed in Printer Properties/Device Settings, Auto Configure support will be deactivated for those changed settings until the system is rebooted.

Solution: To activate the Auto Configure support again, reboot the system. If rebooting is not an option, reinstall the driver and wait several minutes for the Auto Configure to begin.

For the PCL mini-drivers, the paper size "User Defined Size" may appear in some applications as an option. Selecting this paper size will cause the printer to use a default size, such as Letter/A4.

Solution: Ignore this entry. If a custom size is needed, add a Custom Form on the Printer Server Properties dialog box.

Auto-configuration for Printer Memory may not function for some printers with on-board network cards.

Solution: Set the value in Printer Properties manually.

The "Automatically Select" option may not select the proper paper source with the matching size when documents are being printed.

Solution: This is an operating system limitation. Please select the exact paper source you want in Document Properties, or choose the "Auto" option under paper source.